

## ◦ PAM-120A: 120W Modular Mixer Amplifier

Best selling mixer amplifier providing a versatile and flexible solution for many applications including AV, church and high end retail installations.

Optional music modules add to the outstanding features of this market-leading product (see page 16 for details).

### Features:

- 6 Mic/line inputs (3 Pin XLR)
- 2 Module option slots (see page 16 for tuner & CD modules)
- Link input (1/4" jack)
- Amp in (1/4" jack)
- Pre amp out (1/4" jack)
- External chime (screw terminal)
- External mute (screw terminal)
- Individual EQ per input channel
- Individual phantom power (per mic input)
- Priority mic 1, mic 2 (switchable)
- 5 Zone loudspeaker selector
- Bar graph VU metre
- 230v AC/24v DC powered
- Optional 19" rack kit (BKT-PAM)
- 3U high
- Emergency message facility  
*(Only available as custom factory install - contact the sales office on 0115 9770075 for details and prices.)*



◦ 19" Rack Mount Bracket Option: BKT-PAM Bracket

### Specifications:

Model:	PAM-120A:
Output Power	120W RMS @ 100v/70v 120W RMS @ 4Ω
Inputs	6 x Mic/line (3 pin XLR)
Priority	Mic 1, Mic 2
Phantom Power	22v DC individually switched per input
Input Sensitivity/Impedance	Inputs 1~6 -60dB~-16dB 1mv/10kΩ
Frequency Response	80Hz~20KHz
Link In	100mv/10kΩ
Amp In	1v/600Ω
Power Requirement	230v AC 50Hz 24vDC
Dimensions	420(W) x 132(H) x 360(D)mm
Weight	13kg

